
vallenae

Release 0.4.0

Daniel Altmann, Lukas Berbuer (Vallen Systeme GmbH)

Feb 14, 2021

LIBRARY DOCUMENTATION

1 IO	3
1.1 Database classes	3
1.2 Data types	19
1.3 Compression	34
2 Features	35
2.1 Acoustic Emission	35
2.2 Conversion	38
3 Timerpicker	39
3.1 vallenae.timepicker.hinkley	39
3.2 vallenae.timepicker.aic	40
3.3 vallenae.timepicker.energy_ratio	40
3.4 vallenae.timepicker.modified_energy_ratio	41
4 Examples	43
4.1 Read pridb	43
4.2 Read and plot transient data	45
4.3 Timepicker	46
4.4 Timepicker batch processing	51
4.5 Localisation	58
4.6 Go fast with multiprocessing	62
5 Changelog	65
5.1 Unreleased	65
5.2 0.4.0 - 2021-02-14	65
5.3 0.3.0 - 2020-11-05	66
5.4 0.2.4 - 2020-11-01	66
5.5 0.2.3 - 2020-09-01	66
5.6 0.2.2 - 2020-07-10	66
5.7 0.2.1 - 2020-02-10	66
5.8 0.2.0 - 2020-02-06	67
5.9 0.1.0 - 2020-01-24	67
6 ToDos	69
7 Indices and tables	71
Python Module Index	73
Index	75

Extract and analyze Acoustic Emission measurement data.

The IO module `vallenae.io` enables reading (and writing) of Vallen Systeme SQLite database files:

- ***.pridb:** Primary database
- ***.tradb:** Transient data
- ***.trfdb:** Transient features

The remaining modules are system-independent and try to comprise the most common state-of-the-art algorithms in Acoustic Emission:

- `vallenae.features`: Extraction of Acoustic Emission features
- `vallenae.timepicker`: Timepicking algorithms for arrival time estimations

Read/write Vallen Systeme database and setup files.

1.1 Database classes

Classes to read/write pridb, tradb and trfdb database files.

Warning: Writing is still experimental

<i>PriDatabase</i> (filename[, mode])	IO Wrapper for pridb database file.
<i>TraDatabase</i> (filename[, mode, compression])	IO Wrapper for tradb database file.
<i>TrfDatabase</i> (filename[, mode])	IO Wrapper for trfdb (transient feature) database file.

1.1.1 vallenae.io.PriDatabase

```
class vallenae.io.PriDatabase (filename, mode='ro')  
    IO Wrapper for pridb database file.
```

Attributes

<i>connected</i>	Check if connected to SQLite database.
<i>filename</i>	Filename of database.

vallenae.io.PriDatabase.connected

```
property PriDatabase.connected  
    Check if connected to SQLite database.
```

Return type bool

vallennae.io.PriDatabase.filename

property `PriDatabase.filename`
Filename of database.

Return type `str`

Methods

<code>__init__(filename[, mode])</code>	Open pridb database file.
<code>channel()</code>	Get list of channels.
<code>close()</code>	Close database connection.
<code>columns()</code>	Columns of data table.
<code>connection()</code>	Get SQLite connection object.
<code>create(filename)</code>	Create empty pridb.
<code>fieldinfo()</code>	Read fieldinfo table.
<code>globalinfo()</code>	Read globalinfo table.
<code>iread_hits(*[, channel, time_start, ...])</code>	Stream hits with returned iterable.
<code>iread_markers(*[, time_start, time_stop, ...])</code>	Stream markers with returned iterable.
<code>iread_parametric(*[, time_start, time_stop, ...])</code>	Stream parametric data with returned iterable.
<code>iread_status(*[, channel, time_start, ...])</code>	Stream status data with returned iterable.
<code>read(**kwargs)</code>	Read all data set types (hits, markers, parametric data, status data) from pridb to Pandas DataFrame.
<code>read_hits(**kwargs)</code>	Read hits to Pandas DataFrame.
<code>read_markers(**kwargs)</code>	Read marker to Pandas DataFrame.
<code>read_parametric(**kwargs)</code>	Read parametric data to Pandas DataFrame.
<code>read_status(**kwargs)</code>	Read status data to Pandas DataFrame.
<code>rows()</code>	Number of rows in data table.
<code>tables()</code>	Get table names.
<code>write_fieldinfo(field, info)</code>	Write to fieldinfo table.
<code>write_hit(hit)</code>	Write hit to pridb.
<code>write_marker(marker)</code>	Write marker to pridb.
<code>write_parametric(parametric)</code>	Write parametric data to pridb.
<code>write_status(status)</code>	Write status data to pridb.

vallennae.io.PriDatabase.__init__

`PriDatabase.__init__(filename, mode='ro')`
Open pridb database file.

Parameters

- **filename** (`str`) – Path to pridb database file
- **mode** (`str`) – Define database access: “`ro`” (read-only), “`rw`” (read-write), “`rwc`” (read-write and create empty database if it does not exist)

vallenae.io.PriDatabase.channel**PriDatabase.channel()**

Get list of channels.

Return type Set[int]**vallenae.io.PriDatabase.close****PriDatabase.close()**

Close database connection.

vallenae.io.PriDatabase.columns**PriDatabase.columns()**

Columns of data table.

Return type Tuple[str,...]**vallenae.io.PriDatabase.connection****PriDatabase.connection()**

Get SQLite connection object.

Raises RuntimeError – If connection is closed**Return type** Connection**vallenae.io.PriDatabase.create****static PriDatabase.create(filename)**

Create empty pridb.

Parameters `filename` (str) – Path to new pridb database file**vallenae.io.PriDatabase.fieldinfo****PriDatabase.fieldinfo()**

Read fieldinfo table.

The fieldinfo table stores informations about columns of the data table (like units).

Return type Dict[str,Dict[str,Any]]**Returns** Dict of column names and informations (again a dict)

vallennae.io.PriDatabase.globalinfo

PriDatabase.**globalinfo**()

Read globalinfo table.

Return type Dict[str, Any]

vallennae.io.PriDatabase.iread_hits

PriDatabase.**iread_hits**(**, channel=None, time_start=None, time_stop=None, set_id=None, query_filter=None*)

Stream hits with returned iterable.

Parameters

- **channel** (Union[None, int, Sequence[int]]) – None if all channels should be read. Otherwise specify the channel number or a list of channel numbers
- **time_start** (Optional[float]) – Start reading at relative time (in seconds). Start at beginning if *None*
- **time_stop** (Optional[float]) – Stop reading at relative time (in seconds). Read until end if *None*
- **set_id** (Union[None, int, Sequence[int]]) – Read by SetID
- **query_filter** (Optional[str]) – Optional query filter provided as SQL clause, e.g. “Amp > 5000 AND RiseT < 1000”

Return type SizedIterable[HitRecord]

Returns Sized iterable to sequential read hits

vallennae.io.PriDatabase.iread_markers

PriDatabase.**iread_markers**(**, time_start=None, time_stop=None, set_id=None, query_filter=None*)

Stream markers with returned iterable.

Parameters

- **time_start** (Optional[float]) – Start reading at relative time (in seconds). Start at beginning if *None*
- **time_stop** (Optional[float]) – Stop reading at relative time (in seconds). Read until end if *None*
- **set_id** (Union[None, int, Sequence[int]]) – Read by SetID
- **query_filter** (Optional[str]) – Optional query filter provided as SQL clause, e.g. “Number > 11 AND Data LIKE ‘%TimeZone%’”

Return type SizedIterable[MarkerRecord]

Returns Sized iterable to sequential read markers

vallenae.io.PriDatabase.iread_parametric

```
PriDatabase.iread_parametric(*, time_start=None, time_stop=None, set_id=None,
                             query_filter=None)
```

Stream parametric data with returned iterable.

Parameters

- **time_start** (`Optional[float]`) – Start reading at relative time (in seconds). Start at beginning if `None`
- **time_stop** (`Optional[float]`) – Stop reading at relative time (in seconds). Read until end if `None`
- **set_id** (`Union[None, int, Sequence[int]]`) – Read by SetID
- **query_filter** (`Optional[str]`) – Optional query filter provided as SQL clause, e.g. “PA0 >= -5000 AND PA0 < 5000”

Return type `SizedIterable[ParametricRecord]`

Returns Sized iterable to sequential read parametric data

vallenae.io.PriDatabase.iread_status

```
PriDatabase.iread_status(*, channel=None, time_start=None, time_stop=None, set_id=None,
                         query_filter=None)
```

Stream status data with returned iterable.

Parameters

- **channel** (`Union[None, int, Sequence[int]]`) – None if all channels should be read. Otherwise specify the channel number or a list of channel numbers
- **time_start** (`Optional[float]`) – Start reading at relative time (in seconds). Start at beginning if `None`
- **time_stop** (`Optional[float]`) – Stop reading at relative time (in seconds). Read until end if `None`
- **set_id** (`Union[None, int, Sequence[int]]`) – Read by SetID
- **query_filter** (`Optional[str]`) – Optional query filter provided as SQL clause, e.g. “RMS < 300 OR RMS > 500”

Return type `SizedIterable[StatusRecord]`

Returns Sized iterable to sequential read status data

vallenae.io.PriDatabase.read

```
PriDatabase.read(**kwargs)
```

Read all data set types (hits, markers, parametric data, status data) from pridb to Pandas DataFrame.

Parameters `**kwargs` – Arguments passed to `iread_hits`, `iread_markers`, `iread_parametric` and `iread_status`

Return type `DataFrame`

Returns Pandas DataFrame with all pridb data set types

vallenae.io.PriDatabase.read_hits

PriDatabase.**read_hits** (**kwargs)

Read hits to Pandas DataFrame.

Parameters ****kwargs** – Arguments passed to *iread_hits*

Return type DataFrame

Returns Pandas DataFrame with hit data

vallenae.io.PriDatabase.read_markers

PriDatabase.**read_markers** (**kwargs)

Read marker to Pandas DataFrame.

Parameters ****kwargs** – Arguments passed to *iread_markers*

Return type DataFrame

Returns Pandas DataFrame with marker data

vallenae.io.PriDatabase.read_parametric

PriDatabase.**read_parametric** (**kwargs)

Read parametric data to Pandas DataFrame.

Parameters ****kwargs** – Arguments passed to *iread_parametric*

Return type DataFrame

Returns Pandas DataFrame with parametric data

vallenae.io.PriDatabase.read_status

PriDatabase.**read_status** (**kwargs)

Read status data to Pandas DataFrame.

Parameters ****kwargs** – Arguments passed to *iread_status*

Return type DataFrame

Returns Pandas DataFrame with status data

vallenae.io.PriDatabase.rows

PriDatabase.**rows** ()

Number of rows in data table.

Return type int

vallenae.io.PriDatabase.tables

```
PriDatabase.tables()
```

Get table names.

Return type Set[str]

vallenae.io.PriDatabase.write_fieldinfo

```
PriDatabase.write_fieldinfo(field, info)
```

Write to fieldinfo table.

Parameters

- **field** (str) – Column name of data table
- **info** (Dict[str, Any]) – Dict of properties and values, e.g. {"Unit": "[Hz]"}
Raises **ValueError** – If field is not a column of data table

vallenae.io.PriDatabase.write_hit

```
PriDatabase.write_hit(hit)
```

Write hit to pridb.

Caution: *HitRecord.set_id* is ignored and automatically incremented.

Parameters **hit** (HitRecord) – Hit data set

Returns Index (SetID) of inserted row

Todo: Status flag

vallenae.io.PriDatabase.write_marker

```
PriDatabase.write_marker(marker)
```

Write marker to pridb.

Caution: *MarkerRecord.set_id* is ignored and automatically incremented.

Parameters **marker** (MarkerRecord) – Marker data set

Returns Index (SetID) of inserted row

vallenae.io.PriDatabase.write_parametric

```
PriDatabase.write_parametric(parametric)
```

Write parametric data to pridb.

Caution: *ParametricRecord.set_id* is ignored and automatically incremented.

Parameters **parametric** (ParametricRecord) – Parametric data set

Returns Index (SetID) of inserted row

Todo: Status flag

vallenae.io.PriDatabase.write_status

PriDatabase.write_status (*status*)

Write status data to prldb.

Caution: *StatusRecord.set_id* is ignored and automatically incremented.

Parameters **status** (*StatusRecord*) – Status data set

Returns Index (SetID) of inserted row

Todo: Status flag

1.1.2 vallenae.io.TraDatabase

class vallenae.io.TraDatabase (*filename*, *mode='ro'*, *, *compression=False*)

IO Wrapper for tradb database file.

Attributes

<i>connected</i>	Check if connected to SQLite database.
<i>filename</i>	Filename of database.

vallenae.io.TraDatabase.connected

property TraDatabase.**connected**

Check if connected to SQLite database.

Return type *bool*

vallenae.io.TraDatabase.filename

property TraDatabase.**filename**

Filename of database.

Return type *str*

Methods

<code>__init__(filename[, mode, compression])</code>	Open tradb database file.
<code>channel()</code>	Get list of channels.
<code>close()</code>	Close database connection.
<code>columns()</code>	Columns of data table.
<code>connection()</code>	Get SQLite connection object.
<code>create(filename)</code>	Create empty tradb.
<code>fieldinfo()</code>	Read fieldinfo table.
<code>globalinfo()</code>	Read globalinfo table.
<code>iread(*[, channel, time_start, time_stop, ...])</code>	Stream transient data with returned Iterable.
<code>read(**kwargs)</code>	Read transient data to Pandas DataFrame.
<code>read_continuous_wave(channel[, time_start, ...])</code>	Read transient signal of specified channel to a single, continuous array.
<code>read_wave(trai[, time_axis])</code>	Read transient signal for a given TRAI (transient recorder index).
<code>rows()</code>	Number of rows in data table.
<code>tables()</code>	Get table names.
<code>write(trai)</code>	Write transient data to pridb.
<code>write_fieldinfo(field, info)</code>	Write to fieldinfo table.

vallenae.io.TraDatabase.__init__

`TraDatabase.__init__(filename, mode='ro', *, compression=False)`
Open tradb database file.

Parameters

- **filename** (`str`) – Path to tradb database file
- **mode** (`str`) – Define database access: “`ro`” (read-only), “`rw`” (read-write), “`rwc`” (read-write and create empty database if it does not exist)
- **compression** (`bool`) – Enable/disable FLAC compression data BLOBs for writing

vallenae.io.TraDatabase.channel

`TraDatabase.channel()`
Get list of channels.

Return type `Set[int]`

vallenae.io.TraDatabase.close

`TraDatabase.close()`
Close database connection.

vallennae.io.TraDatabase.columns

TraDatabase.**columns**()
Columns of data table.

Return type Tuple[str,...]

vallennae.io.TraDatabase.connection

TraDatabase.**connection**()
Get SQLite connection object.

Raises `RuntimeError` – If connection is closed

Return type Connection

vallennae.io.TraDatabase.create

static TraDatabase.**create**(filename)
Create empty tradb.

Parameters `filename` (str) – Path to new tradb database file

vallennae.io.TraDatabase.fieldinfo

TraDatabase.**fieldinfo**()
Read fieldinfo table.

The fieldinfo table stores informations about columns of the data table (like units).

Return type Dict[str,Dict[str,Any]]

Returns Dict of column names and informations (again a dict)

vallennae.io.TraDatabase.globalinfo

TraDatabase.**globalinfo**()
Read globalinfo table.

Return type Dict[str,Any]

vallennae.io.TraDatabase.iread

TraDatabase.**iread**(*args, channel=None, time_start=None, time_stop=None, trai=None, query_filter=None)
Stream transient data with returned Iterable.

Parameters

- **channel** (Union[None, int, Sequence[int]]) – None if all channels should be read. Otherwise specify the channel number or a list of channel numbers
- **time_start** (Optional[float]) – Start reading at relative time (in seconds). Start at beginning if `None`
- **time_stop** (Optional[float]) – Stop reading at relative time (in seconds). Read until end if `None`

- **trai** (`Union[None, int, Sequence[int]]`) – Read data by TRAI (transient recorder index)
- **query_filter** (`Optional[str]`) – Optional query filter provided as SQL clause, e.g. “Pretrigger == 500 AND Samples >= 1024”

Return type `SizedIterable[TraRecord]`

Returns Sized iterable to sequential read transient data

vallenae.io.TraDatabase.read

`TraDatabase.read(**kwargs)`

Read transient data to Pandas DataFrame.

Parameters `**kwargs` – Arguments passed to `iread`

Return type `DataFrame`

Returns Pandas DataFrame with transient data

vallenae.io.TraDatabase.read_continuous_wave

`TraDatabase.read_continuous_wave(channel, time_start=None, time_stop=None, *, time_axis=True, show_progress=True)`

Read transient signal of specified channel to a single, continuous array.

The signal is exactly cropped to the given time range. Time gaps are filled with 0's.

Parameters

- **channel** (`int`) – Channel number to read
- **time_start** (`Optional[float]`) – Start reading at relative time (in seconds). Start at beginning if `None`
- **time_stop** (`Optional[float]`) – Stop reading at relative time (in seconds). Read until end if `None`
- **time_axis** (`bool`) – Create the corresponding time axis. Default: `True`
- **show_progress** (`bool`) – Show progress bar. Default: `True`

Return type `Union[Tuple[ndarray, ndarray], Tuple[ndarray, int]]`

Returns

If `time_axis` is `True`

- Array with transient signal
- Time axis

If `time_axis` is `False`

- Array with transient signal
- Samplerate

vallennae.io.TraDatabase.read_wave

TraDatabase.**read_wave** (*trai*, *time_axis=True*)

Read transient signal for a given TRAI (transient recorder index).

This method is useful in combination with *PriDatabase.read_hits*, that will store the TRAI in a DataFrame.

Parameters

- **trai** (`int`) – Transient recorder index (unique key between pridb and tradb)
- **time_axis** (`bool`) – Create the corresponding time axis. Default: *True*

Return type `Union[Tuple[ndarray, ndarray], Tuple[ndarray, int]]`

Returns

If *time_axis* is *True*

- Array with transient signal
- Time axis

If *time_axis* is *False*

- Array with transient signal
- Samplerate

vallennae.io.TraDatabase.rows

TraDatabase.**rows** ()

Number of rows in data table.

Return type `int`

vallennae.io.TraDatabase.tables

TraDatabase.**tables** ()

Get table names.

Return type `Set[str]`

vallennae.io.TraDatabase.write

TraDatabase.**write** (*tra*)

Write transient data to pridb.

Parameters **tra** (`TraRecord`) – Transient data set

Return type `int`

Returns Index (SetID) of inserted row

Todo: Status flag

vallenae.io.TraDatabase.write_fieldinfo**TraDatabase.write_fieldinfo**(*field, info*)

Write to fieldinfo table.

Parameters

- **field** (`str`) – Column name of data table
- **info** (`Dict[str, Any]`) – Dict of properties and values, e.g. {"Unit": "[Hz]"}

Raises ValueError – If field is not a column of data table**1.1.3 vallenae.io.TrfDatabase****class vallenae.io.TrfDatabase**(*filename, mode='ro'*)

IO Wrapper for trfdb (transient feature) database file.

Attributes

<i>connected</i>	Check if connected to SQLite database.
<i>filename</i>	Filename of database.

vallenae.io.TrfDatabase.connected**property TrfDatabase.connected**

Check if connected to SQLite database.

Return type `bool`**vallenae.io.TrfDatabase.filename****property TrfDatabase.filename**

Filename of database.

Return type `str`**Methods**

<i>__init__(filename[, mode])</i>	Open trfdb database file.
<i>close()</i>	Close database connection.
<i>columns()</i>	Columns of data table.
<i>connection()</i>	Get SQLite connection object.
<i>create(filename)</i>	Create empty trfdb.
<i>fieldinfo()</i>	Read fieldinfo table.
<i>globalinfo()</i>	Read globalinfo table.
<i>iread(*[, trai])</i>	Stream features with returned iterable.
<i>read(*[, trai])</i>	Read features to Pandas DataFrame.
<i>rows()</i>	Number of rows in data table.
<i>tables()</i>	Get table names.

continues on next page

Table 7 – continued from previous page

<code>write(feature_set)</code>	Write feature record to trfdb.
<code>write_fieldinfo(field, info)</code>	Write to fieldinfo table.

vallennae.io.TrfDatabase.__init__

`TrfDatabase.__init__(filename, mode='ro')`
Open trfdb database file.

Parameters

- **filename** (`str`) – Path to trfdb database file
- **mode** (`str`) – Define database access: “`ro`” (read-only), “`rw`” (read-write), “`rwc`” (read-write and create empty database if it does not exist)

vallennae.io.TrfDatabase.close

`TrfDatabase.close()`
Close database connection.

vallennae.io.TrfDatabase.columns

`TrfDatabase.columns()`
Columns of data table.
Return type `Tuple[str, ...]`

vallennae.io.TrfDatabase.connection

`TrfDatabase.connection()`
Get SQLite connection object.
Raises `RuntimeError` – If connection is closed
Return type `Connection`

vallennae.io.TrfDatabase.create

`static TrfDatabase.create(filename)`
Create empty trfdb.
Parameters `filename` (`str`) – Path to new trfdb database file

vallennae.io.TrfDatabase.fieldinfo

TrfDatabase.**fieldinfo**()

Read fieldinfo table.

The fieldinfo table stores informations about columns of the data table (like units).

Return type Dict[str, Dict[str, Any]]

Returns Dict of column names and informations (again a dict)

vallennae.io.TrfDatabase.globalinfo

TrfDatabase.**globalinfo**()

Read globalinfo table.

Return type Dict[str, Any]

vallennae.io.TrfDatabase.iread

TrfDatabase.**iread**(*, trai=None)

Stream features with returned iterable.

Parameters **trai** (Union[None, int, Sequence[int]]) – Read data by TRAI (transient recorder index)

Return type SizedIterable[FeatureRecord]

Returns Sized iterable to sequential read features

vallennae.io.TrfDatabase.read

TrfDatabase.**read**(*, trai=None)

Read features to Pandas DataFrame.

Parameters **trai** (Union[None, int, Sequence[int]]) – Read data by TRAI (transient recorder index)

Return type DataFrame

Returns Pandas DataFrame with features

vallennae.io.TrfDatabase.rows

TrfDatabase.**rows**()

Number of rows in data table.

Return type int

vallennae.io.TrfDatabase.tables**TrfDatabase.tables()**

Get table names.

Return type Set[str]**vallennae.io.TrfDatabase.write****TrfDatabase.write(feature_set)**

Write feature record to trfdb.

Parameters **feature_set** (FeatureRecord) – Feature set**Return type** int**Returns** Index (trai) of inserted row**vallennae.io.TrfDatabase.write_fieldinfo****TrfDatabase.write_fieldinfo(field, info)**

Write to fieldinfo table.

Parameters

- **field** (str) – Column name of data table
- **info** (Dict[str, Any]) – Dict of properties and values, e.g. {"Unit": "[Hz]"}
Raises **ValueError** – If field is not a column of data table

All database classes implement two different interfaces to access data:

Standard read_*Read data to `pandas.DataFrame`, e.g. with `PriDatabase.read_hits`

```
>>> pridb = vae.io.PriDatabase("./examples/steel_plate/sample.pridb")
>>> df = pridb.read_hits()  # save all hits to pandas dataframe
>>> df[["time", "channel"]]
   time  channel
set_id
10     3.992771      3
11     3.992775      2
12     3.992813      4
13     3.992814      1
```

Streaming iread_*Iterate through the data row by row. This is a memory-efficient solution ideal for batch processing. The return types are specific `typing.NamedTuple`, see [Data types](#).Example with `PriDatabase.iread_hits`:

```
>>> pridb = vae.io.PriDatabase("./examples/steel_plate/sample.pridb")
>>> for hit in pridb.iread_hits():
...     print(f"time: {hit.time:.4f}, channel: {hit.channel}")
...
time: 3.9928,    channel: 3
time: 3.9928,    channel: 2
```

(continues on next page)

(continued from previous page)

```
time: 3.9928,    channel: 4
time: 3.9928,    channel: 1
>>> type(hit)
<class 'vallenae.io.datatypes.HitRecord'>
```

1.2 Data types

Records of the database are represented as `typing.NamedTuple`. Each record implements a class method `from_sql` to init from a SQLite row dictionary (column name: value).

<code>HitRecord</code> (time, channel, param_id, ...)	Hit record in pridb (SetType = 2).
<code>MarkerRecord</code> (time, set_type, data, number, ...)	Marker record in pridb (SetType = 4, 5, 6).
<code>StatusRecord</code> (time, channel, param_id, ...)	Status data record in pridb (SetType = 3).
<code>ParametricRecord</code> (time, param_id, set_id, ...)	Parametric data record in pridb (SetType = 1).
<code>TraRecord</code> (time, channel, param_id, ...)	Transient data record in tradb.
<code>FeatureRecord</code> (trai, features, float[])	Transient feature record in trfdb.

1.2.1 vallenae.io.HitRecord

```
class vallenae.io.HitRecord(time: float, channel: int, param_id: int, amplitude: float, duration: float, energy: float, rms: float, set_id: Optional[int] = None, threshold: Optional[float] = None, rise_time: Optional[float] = None, signal_strength: Optional[float] = None, counts: Optional[int] = None, trai: Optional[int] = None, cascade_hits: Optional[int] = None, cascade_counts: Optional[int] = None, cascade_energy: Optional[int] = None, cascade_signal_strength: Optional[int] = None)
```

Hit record in pridb (SetType = 2).

Attributes

<code>amplitude</code>	Peak amplitude in volts
<code>cascade_counts</code>	Summed counts of hits in the same hit-cascade
<code>cascade_energy</code>	Summed energy of hits in the same hit-cascade
<code>cascade_hits</code>	Total number of hits in the same hit-cascade
<code>cascade_signal_strength</code>	disable=line-too-long
<code>channel</code>	Channel number
<code>counts</code>	Number of positive threshold crossings
<code>duration</code>	Hit duration in seconds
<code>energy</code>	Energy (EN 1330-9) in eu (1e-14 V ² s)
<code>param_id</code>	Parameter ID of table ae_params for ADC value conversion
<code>rise_time</code>	Rise time in seconds
<code>rms</code>	RMS of the noise before the hit in volts
<code>set_id</code>	Unique identifier for data set in pridb
<code>signal_strength</code>	Signal strength in nVs (1e-9 Vs)
<code>threshold</code>	Threshold amplitude in volts

continues on next page

Table 9 – continued from previous page

<i>time</i>	Time in seconds
<i>trai</i>	Transient recorder index (foreign key between pridb and tradb)

vallennae.io.HitRecord.amplitude

property HitRecord.**amplitude**
Peak amplitude in volts

vallennae.io.HitRecord.cascade_counts

property HitRecord.**cascade_counts**
Summed counts of hits in the same hit-cascade

vallennae.io.HitRecord.cascade_energy

property HitRecord.**cascade_energy**
Summed energy of hits in the same hit-cascade

vallennae.io.HitRecord.cascade_hits

property HitRecord.**cascade_hits**
Total number of hits in the same hit-cascade

vallennae.io.HitRecord.cascade_signal_strength

property HitRecord.**cascade_signal_strength**
disable=line-too-long
Type Summed signal strength of hits in the same hit-cascade # noqa # pylint

vallennae.io.HitRecord.channel

property HitRecord.**channel**
Channel number

vallennae.io.HitRecord.counts

property HitRecord.**counts**
Number of positive threshold crossings

vallennae.io.HitRecord.duration

property HitRecord.duration
Hit duration in seconds

vallennae.io.HitRecord.energy

property HitRecord.energy
Energy (EN 1330-9) in eu (1e-14 V²s)

vallennae.io.HitRecord.param_id

property HitRecord.param_id
Parameter ID of table ae_params for ADC value conversion

vallennae.io.HitRecord.rise_time

property HitRecord.rise_time
Rise time in seconds

vallennae.io.HitRecord.rms

property HitRecord.rms
RMS of the noise before the hit in volts

vallennae.io.HitRecord.set_id

property HitRecord.set_id
Unique identifier for data set in pridb

vallennae.io.HitRecord.signal_strength

property HitRecord.signal_strength
Signal strength in nVs (1e-9 Vs)

vallennae.io.HitRecord.threshold

property HitRecord.threshold
Threshold amplitude in volts

vallennae.io.HitRecord.time

property HitRecord.time
Time in seconds

vallennae.io.HitRecord.trai

property HitRecord.trai
Transient recorder index (foreign key between pridb and tradb)

Methods

<code>__init__(value, /)</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	Create HitRecord from SQL row.
<code>index(value[, start, stop])</code>	Return first index of value.

vallennae.io.HitRecord.__init__

HitRecord.__init__(value, /)
Initialize self. See help(type(self)) for accurate signature.

vallennae.io.HitRecord.count

HitRecord.count(value, /)
Return number of occurrences of value.

vallennae.io.HitRecord.from_sql

classmethod HitRecord.from_sql(row)
Create HitRecord from SQL row.
Parameters `row(Dict[str, Any])` – Dict of column names and values
Return type HitRecord

vallennae.io.HitRecord.index

HitRecord.index(value, start=0, stop=9223372036854775807, /)
Return first index of value.
Raises ValueError if the value is not present.

1.2.2 vallenae.io.MarkerRecord

```
class vallenae.io.MarkerRecord(time: float, set_type: int, data: str, number: Optional[int] = None, set_id: Optional[int] = None)
```

Marker record in pridb (SetType = 4, 5, 6).

A marker can have different meanings depending on its SetType:

- 4: label
- 5: datetime data set, as it is inserted whenever recording is started by software
- 6: a section start marker. E.g. new sections are started, if acquisition settings changed

Attributes

<i>data</i>	Content of marker (label text or datetime)
<i>number</i>	Marker number
<i>set_id</i>	Unique identifier for data set in pridb
<i>set_type</i>	Marker type (see above)
<i>time</i>	Time in seconds

vallenae.io.MarkerRecord.data

```
property MarkerRecord.data
```

Content of marker (label text or datetime)

vallenae.io.MarkerRecord.number

```
property MarkerRecord.number
```

Marker number

vallenae.io.MarkerRecord.set_id

```
property MarkerRecord.set_id
```

Unique identifier for data set in pridb

vallenae.io.MarkerRecord.set_type

```
property MarkerRecord.set_type
```

Marker type (see above)

vallennae.io.MarkerRecord.time

property MarkerRecord.time
Time in seconds

Methods

<code>__init__()</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	Create MarkerRecord from SQL row.
<code>index(value[, start, stop])</code>	Return first index of value.

vallennae.io.MarkerRecord.__init__

MarkerRecord.__init__()
Initialize self. See help(type(self)) for accurate signature.

vallennae.io.MarkerRecord.count

MarkerRecord.count (value, /)
Return number of occurrences of value.

vallennae.io.MarkerRecord.from_sql

classmethod MarkerRecord.from_sql (row)
Create MarkerRecord from SQL row.
Parameters `row` (Dict[str, Any]) – Dict of column names and values
Return type MarkerRecord

vallennae.io.MarkerRecord.index

MarkerRecord.index (value, start=0, stop=9223372036854775807, /)
Return first index of value.
Raises ValueError if the value is not present.

1.2.3 vallennae.io.StatusRecord

```
class vallennae.io.StatusRecord(time: float, channel: int, param_id: int, energy: float, rms: float, set_id: Optional[int] = None, threshold: Optional[float] = None, signal_strength: Optional[float] = None)
```

Status data record in pridb (SetType = 3).

Attributes

<i>channel</i>	Channel number
<i>energy</i>	Energy (EN 1330-9) in eu (1e-14 V ² s)
<i>param_id</i>	Parameter ID of table ae_params for ADC value conversion
<i>rms</i>	RMS in volts
<i>set_id</i>	Unique identifier for data set in pridb
<i>signal_strength</i>	Signal strength in nVs (1e-9 Vs)
<i>threshold</i>	Threshold amplitude in volts
<i>time</i>	Time in seconds

vallennae.io.StatusRecord.channel

property StatusRecord.**channel**
Channel number

vallennae.io.StatusRecord.energy

property StatusRecord.**energy**
Energy (EN 1330-9) in eu (1e-14 V²s)

vallennae.io.StatusRecord.param_id

property StatusRecord.**param_id**
Parameter ID of table ae_params for ADC value conversion

vallennae.io.StatusRecord.rms

property StatusRecord.**rms**
RMS in volts

vallennae.io.StatusRecord.set_id

property StatusRecord.**set_id**
Unique identifier for data set in pridb

vallennae.io.StatusRecord.signal_strength

property StatusRecord.**signal_strength**
Signal strength in nVs (1e-9 Vs)

vallennae.io.StatusRecord.threshold

property StatusRecord.**threshold**
Threshold amplitude in volts

vallennae.io.StatusRecord.time

property StatusRecord.**time**
Time in seconds

Methods

<code>__init__(value, /)</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	Create StatusRecord from SQL row.
<code>index(value[, start, stop])</code>	Return first index of value.

vallennae.io.StatusRecord.__init__

StatusRecord.**__init__(value, /)**
Initialize self. See help(type(self)) for accurate signature.

vallennae.io.StatusRecord.count

StatusRecord.**count (value, /)**
Return number of occurrences of value.

vallennae.io.StatusRecord.from_sql

classmethod StatusRecord.**from_sql (row)**
Create StatusRecord from SQL row.
Parameters `row (Dict[str, Any])` – Dict of column names and values
Return type StatusRecord

vallennae.io.StatusRecord.index

StatusRecord.**index (value, start=0, stop=9223372036854775807, /)**
Return first index of value.
Raises ValueError if the value is not present.

1.2.4 vallenae.io.ParametricRecord

```
class vallenae.io.ParametricRecord(time: float, param_id: int, set_id: Optional[int] = None,  

                                    pctd: Optional[int] = None, pcta: Optional[int] = None,  

                                    pa0: Optional[int] = None, pa1: Optional[int] = None,  

                                    pa2: Optional[int] = None, pa3: Optional[int] = None,  

                                    pa4: Optional[int] = None, pa5: Optional[int] = None,  

                                    pa6: Optional[int] = None, pa7: Optional[int] = None)
```

Parametric data record in pridb (SetType = 1).

Attributes

<i>pa0</i>	Amplitude of parametric input 0 in volts
<i>pa1</i>	Amplitude of parametric input 1 in volts
<i>pa2</i>	Amplitude of parametric input 2 in volts
<i>pa3</i>	Amplitude of parametric input 3 in volts
<i>pa4</i>	Amplitude of parametric input 4 in volts
<i>pa5</i>	Amplitude of parametric input 5 in volts
<i>pa6</i>	Amplitude of parametric input 6 in volts
<i>pa7</i>	Amplitude of parametric input 7 in volts
<i>param_id</i>	Parameter ID of table ae_params for ADC value conversion
<i>pcta</i>	Analog hysteresis counter
<i>pctd</i>	Digital counter value
<i>set_id</i>	Unique identifier for data set in pridb
<i>time</i>	Time in seconds

vallenae.io.ParametricRecord.pa0

```
property ParametricRecord.pa0
Amplitude of parametric input 0 in volts
```

vallenae.io.ParametricRecord.pa1

```
property ParametricRecord.pa1
Amplitude of parametric input 1 in volts
```

vallenae.io.ParametricRecord.pa2

```
property ParametricRecord.pa2
Amplitude of parametric input 2 in volts
```

vallennae.io.ParametricRecord.pa3

property ParametricRecord.pa3
Amplitude of parametric input 3 in volts

vallennae.io.ParametricRecord.pa4

property ParametricRecord.pa4
Amplitude of parametric input 4 in volts

vallennae.io.ParametricRecord.pa5

property ParametricRecord.pa5
Amplitude of parametric input 5 in volts

vallennae.io.ParametricRecord.pa6

property ParametricRecord.pa6
Amplitude of parametric input 6 in volts

vallennae.io.ParametricRecord.pa7

property ParametricRecord.pa7
Amplitude of parametric input 7 in volts

vallennae.io.ParametricRecord.param_id

property ParametricRecord.param_id
Parameter ID of table ae_params for ADC value conversion

vallennae.io.ParametricRecord.pcta

property ParametricRecord.pcta
Analog hysteresis counter

vallennae.io.ParametricRecord.pctd

property ParametricRecord.pctd
Digital counter value

vallennae.io.ParametricRecord.set_id

property ParametricRecord.**set_id**
 Unique identifier for data set in pridb

vallennae.io.ParametricRecord.time

property ParametricRecord.**time**
 Time in seconds

Methods

<code>__init__()</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	Create ParametricRecord from SQL row.
<code>index(value[, start, stop])</code>	Return first index of value.

vallennae.io.ParametricRecord.__init__

ParametricRecord.**__init__()**
 Initialize self. See help(type(self)) for accurate signature.

vallennae.io.ParametricRecord.count

ParametricRecord.**count** (*value*, /)
 Return number of occurrences of value.

vallennae.io.ParametricRecord.from_sql

classmethod ParametricRecord.**from_sql** (*row*)
 Create ParametricRecord from SQL row.
Parameters `row (Dict[str, Any])` – Dict of column names and values
Return type ParametricRecord

vallennae.io.ParametricRecord.index

ParametricRecord.**index** (*value*, *start*=0, *stop*=9223372036854775807, /)
 Return first index of value.
 Raises ValueError if the value is not present.

1.2.5 vallennae.io.TraRecord

```
class vallennae.io.TraRecord(time: float, channel: int, param_id: int, pretrigger: int, threshold: float, samplerate: int, samples: int, data_format: int, data: numpy.ndarray, trai: Optional[int] = None, rms: Optional[float] = None)
```

Transient data record in tradb.

Todo: Remove RMS

Attributes

<i>channel</i>	Channel number
<i>data</i>	Transient signal in volts
<i>data_format</i>	Data format (0 = uncompressed, 2 = FLAC compression)
<i>param_id</i>	Parameter ID of table tr_params for ADC value conversion
<i>pretrigger</i>	Pretrigger samples
<i>rms</i>	RMS of the noise before the hit
<i>samplerate</i>	Samplerate in Hz
<i>samples</i>	Number of samples
<i>threshold</i>	Threshold amplitude in volts
<i>time</i>	Time in seconds
<i>trai</i>	Transient recorder index (foreign key between pridb and tradb)

vallennae.io.TraRecord.channel

```
property TraRecord.channel  
    Channel number
```

vallennae.io.TraRecord.data

```
property TraRecord.data  
    Transient signal in volts
```

vallennae.io.TraRecord.data_format

```
property TraRecord.data_format  
    Data format (0 = uncompressed, 2 = FLAC compression)
```

vallennae.io.TraRecord.param_id**property** TraRecord.**param_id**

Parameter ID of table tr_params for ADC value conversion

vallennae.io.TraRecord.pretrigger**property** TraRecord.**pretrigger**

Pretrigger samples

vallennae.io.TraRecord.rms**property** TraRecord.**rms**

RMS of the noise before the hit

vallennae.io.TraRecord.samplerate**property** TraRecord.**samplerate**

Samplerate in Hz

vallennae.io.TraRecord.samples**property** TraRecord.**samples**

Number of samples

vallennae.io.TraRecord.threshold**property** TraRecord.**threshold**

Threshold amplitude in volts

vallennae.io.TraRecord.time**property** TraRecord.**time**

Time in seconds

vallennae.io.TraRecord.trai**property** TraRecord.**trai**

Transient recorder index (foreign key between pridb and tradb)

Methods

<code>__init__()</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	rtype TraRecord
<code>index(value[, start, stop])</code>	Return first index of value.

vallennae.io.TraRecord.__init__

`TraRecord.__init__()`
Initialize self. See help(type(self)) for accurate signature.

vallennae.io.TraRecord.count

`TraRecord.count (value, /)`
Return number of occurrences of value.

vallennae.io.TraRecord.from_sql

`classmethod TraRecord.from_sql (row)`
Return type TraRecord

vallennae.io.TraRecord.index

`TraRecord.index (value, start=0, stop=9223372036854775807, /)`
Return first index of value.
Raises ValueError if the value is not present.

1.2.6 vallennae.io.FeatureRecord

`class vallennae.io.FeatureRecord (trai: int, features: Dict[str, float])`
Transient feature record in trfdb.

Attributes

<code>features</code>	Feature dictionary (feature name -> value)
<code>trai</code>	Transient recorder index

vallenae.io.FeatureRecord.features

property FeatureRecord.**features**
 Feature dictionary (feature name -> value)

vallenae.io.FeatureRecord.trai

property FeatureRecord.**trai**
 Transient recorder index

Methods

<code>__init__(value[, /])</code>	Initialize self.
<code>count(value, /)</code>	Return number of occurrences of value.
<code>from_sql(row)</code>	rtype FeatureRecord
<code>index(value[, start, stop])</code>	Return first index of value.

vallenae.io.FeatureRecord.__init__

FeatureRecord.**__init__(value[, /])**
 Initialize self. See help(type(self)) for accurate signature.

vallenae.io.FeatureRecord.count

FeatureRecord.**count(value, /)**
 Return number of occurrences of value.

vallenae.io.FeatureRecord.from_sql

classmethod FeatureRecord.**from_sql(row)**
Return type FeatureRecord

vallenae.io.FeatureRecord.index

FeatureRecord.**index(value, start=0, stop=9223372036854775807, /)**
 Return first index of value.
 Raises ValueError if the value is not present.

1.3 Compression

Transient signals in the tradb are stored as BLOBs of 16-bit ADC values – either uncompressed or compressed (FLAC). Following functions convert between BLOBs and arrays of voltage values.

<code>decode_data_blob(data_blob, data_format, ...)</code>	Decodes (compressed) 16-bit ADC values from BLOB to array of voltage values.
<code>encode_data_blob(data, data_format, ...)</code>	Encodes array of voltage values to BLOB of 16-bit ADC values for memory-efficient storage.

1.3.1 vallenae.io.decode_data_blob

`vallenae.io.decode_data_blob(data_blob, data_format, factor_millivolts)`

Decodes (compressed) 16-bit ADC values from BLOB to array of voltage values.

Parameters

- `data_blob (bytes)` – Blob from tradb
- `data_format (int)` –
 - 0: uncompressed
 - 2: FLAC compression
- `factor_millivolts (float)` – Factor from int16 representation to millivolts. Stored in tradb -> tr_params as ‘TR_mV’

Return type `ndarray`

Returns Array of voltage values

1.3.2 vallenae.io.encode_data_blob

`vallenae.io.encode_data_blob(data, data_format, factor_millivolts)`

Encodes array of voltage values to BLOB of 16-bit ADC values for memory-efficient storage.

Parameters

- `data (ndarray)` – Array with voltage values
- `data_format (int)` –
 - 0: uncompressed
 - 2: FLAC compression
- `factor_millivolts (float)` – Factor from int16 representation to millivolts. Stored in tradb -> tr_params as ‘TR_mV’

Return type `bytes`

Returns Data blob

FEATURES

2.1 Acoustic Emission

<code>peak_amplitude(data)</code>	Compute maximum absolute amplitude.
<code>peak_amplitude_index(data)</code>	Compute index of peak amplitude.
<code>is_above_threshold(data, threshold)</code>	Checks if absolute amplitudes are above threshold.
<code>first_threshold_crossing(data, threshold)</code>	Compute index of first threshold crossing.
<code>rise_time(data, threshold, samplerate[, ...])</code>	Compute the rise time.
<code>energy(data, samplerate)</code>	Compute the energy of a hit.
<code>signal_strength(data, samplerate)</code>	Compute the signal strength of a hit.
<code>counts(data, threshold)</code>	Compute the number of positive threshold crossings of a hit (counts).
<code>rms(data)</code>	Compute the root mean square (RMS) of an array.

2.1.1 vallenae.features.peak_amplitude

```
vallenae.features.peak_amplitude(data)
```

Compute maximum absolute amplitude.

Parameters `data` (`ndarray`) – Input array

Return type `float`

Returns Peak amplitude of the input array

2.1.2 vallenae.features.peak_amplitude_index

```
vallenae.features.peak_amplitude_index(data)
```

Compute index of peak amplitude.

Parameters `data` (`ndarray`) – Input array

Return type `int`

Returns Index of peak amplitude

2.1.3 vallenae.features.is_above_threshold

vallenae.features.**is_above_threshold**(*data*, *threshold*)

Checks if absolute amplitudes are above threshold.

Parameters

- **data** (`ndarray`) – Input array
- **threshold** (`float`) – Threshold amplitude

Return type `bool`

Returns True if input array is above threshold, otherwise False

2.1.4 vallenae.features.first_threshold_crossing

vallenae.features.**first_threshold_crossing**(*data*, *threshold*)

Compute index of first threshold crossing.

Parameters

- **data** (`ndarray`) – Input array
- **threshold** (`float`) – Threshold amplitude

Return type `Optional[int]`

Returns Index of first threshold crossing. None if threshold was not exceeded

2.1.5 vallenae.features.rise_time

vallenae.features.**rise_time**(*data*, *threshold*, *samplerate*, *first_crossing=None*, *index_peak=None*)

Compute the rise time.

The rise time is the time between the first threshold crossing and the peak amplitude.

Parameters

- **data** (`ndarray`) – Input array (hit)
- **threshold** (`float`) – Threshold amplitude (in volts)
- **samplerate** (`int`) – Sample rate of the input array
- **first_crossing** (`Optional[int]`) – Precomputed index of first threshold crossing to save computation time
- **index_peak** (`Optional[int]`) – Precomputed index of peak amplitude to save computation time

Return type `float`

2.1.6 vallenae.features.energy

`vallenae.features.energy`(*data, samplerate*)

Compute the energy of a hit.

Energy is the integral of the squared AE-signal over time (EN 1330-9). The unit of energy is eu. 1 eu corresponds to 1e-14 V²s.

Parameters

- **data** (`ndarray`) – Input array (hit)
- **samplerate** (`int`) – Sample rate of input array in Hz

Return type `float`

Returns Energy of input array (hit)

2.1.7 vallenae.features.signal_strength

`vallenae.features.signal_strength`(*data, samplerate*)

Compute the signal strength of a hit.

Signal strength is the integral of the rectified AE-signal over time. The unit of Signal Strength is nVs (1e-9 Vs).

Parameters

- **data** (`ndarray`) – Input array (hit)
- **samplerate** (`int`) – Sample rate of input array in Hz

Return type `float`

Returns Signal strength of input array (hit)

2.1.8 vallenae.features.counts

`vallenae.features.counts`(*data, threshold*)

Compute the number of positive threshold crossings of a hit (counts).

Parameters

- **data** (`ndarray`) – Input array
- **threshold** (`float`) – Threshold amplitude

Return type `int`

Returns Number of positive threshold crossings

2.1.9 vallenae.features.rms

`vallenae.features.rms`(*data*)

Compute the root mean square (RMS) of an array.

Parameters **data** (`ndarray`) – Input array

Return type `float`

Returns RMS of the input array

References

https://en.wikipedia.org/wiki/Root_mean_square

2.2 Conversion

<code>amplitude_to_db(amplitude[, reference])</code>	Convert amplitude from volts to decibel (dB).
<code>db_to_amplitude(amplitude_db[, reference])</code>	Convert amplitude from decibel (dB) to volts.

2.2.1 vallenae.features.amplitude_to_db

`vallenae.features.amplitude_to_db(amplitude, reference=1e-06)`

Convert amplitude from volts to decibel (dB).

Parameters

- **amplitude** (`float`) – Amplitude in volts
- **reference** (`float`) – Reference amplitude. Defaults to 1 μ V for dB(AE)

Return type `float`

Returns Amplitude in dB(ref)

2.2.2 vallenae.features.db_to_amplitude

`vallenae.features.db_to_amplitude(amplitude_db, reference=1e-06)`

Convert amplitude from decibel (dB) to volts.

Parameters

- **amplitude_db** (`float`) – Amplitude in dB
- **reference** (`float`) – Reference amplitude. Defaults to 1 μ V for dB(AE)

Return type `float`

Returns Amplitude in volts

TIMERPICKER

The determination of signal arrival times has a major influence on the localization accuracy. Usually, arrival times are determined by the first threshold crossing (either fixed or adaptive). Following popular methods have been proposed in the past to automatically pick time of arrivals:

<code>hinkley(arr[, alpha])</code>	Hinkley criterion for arrival time estimation.
<code>aic(arr)</code>	Akaike Information Criterion (AIC) for arrival time estimation.
<code>energy_ratio(arr[, win_len])</code>	Energy ratio for arrival time estimation.
<code>modified_energy_ratio(arr[, win_len])</code>	Modified energy ratio method for arrival time estimation.

3.1 vallenae.timepicker.hinkley

`vallenae.timepicker.hinkley(arr, alpha=5)`

Hinkley criterion for arrival time estimation.

The Hinkley criterion is defined as the partial energy of the signal (cumulative square sum) with an applied negative trend (characterized by alpha).

The starting value of alpha is reduced iteratively to avoid wrong picks within the pre-trigger part of the signal. Usually alpha values are chosen to be between 2 and 200 to ensure minimal delay. The chosen alpha value for the Hinkley criterion influences the results significantly.

Parameters

- `arr` (`ndarray`) – Transient signal of hit
- `alpha` (`int`) – Divisor of the negative trend. Default: 5

Return type `Tuple[ndarray, int]`

Returns

- Array with computed detection function
- Index of the estimated arrival time (max value)

Todo: Weak performance, if used with default parameter alpha

References

- Molenda, M. (2016). Acoustic Emission monitoring of laboratory hydraulic fracturing experiments. Ruhr-Universität Bochum.
- van Rijn, N. (2017). Investigating the Behaviour of Acoustic Emission Waves Near Cracks: Using the Finite Element Method. Delft University of Technology.

3.2 vallenaе.timepicker.aic

vallenaе.timepicker.**aic**(arr)

Akaike Information Criterion (AIC) for arrival time estimation.

The AIC picker basically models the signal as an autoregressive (AR) process. A typical AE signal can be subdivided into two parts. The first part containing noise and the second part containing noise and the AE signal. Both parts of the signal contain non deterministic parts (noise) describable by a Gaussian distribution.

Parameters arr (`ndarray`) – Transient signal of hit

Return type `Tuple[ndarray, int]`

Returns

- Array with computed detection function
- Index of the estimated arrival time (max value)

References

- Molenda, M. (2016). Acoustic Emission monitoring of laboratory hydraulic fracturing experiments. Ruhr-Universität Bochum.
- Bai, F., Gagar, D., Foote, P., & Zhao, Y. (2017). Comparison of alternatives to amplitude thresholding for onset detection of acoustic emission signals. Mechanical Systems and Signal Processing, 84, 717–730.
- van Rijn, N. (2017). Investigating the Behaviour of Acoustic Emission Waves Near Cracks: Using the Finite Element Method. Delft University of Technology.

3.3 vallenaе.timepicker.energy_ratio

vallenaе.timepicker.**energy_ratio**(arr, win_len=100)

Energy ratio for arrival time estimation.

Method based on preceding and following energy collection windows.

Parameters

- arr (`ndarray`) – Transient signal of hit
- win_len (`int`) – Samples of sliding windows. Default: 100

Return type `Tuple[ndarray, int]`

Returns

- Array with computed detection function
- Index of the estimated arrival time (max value)

References

- Han, L., Wong, J., & Bancroft, J. C. (2009). Time picking and random noise reduction on microseismic data. CREWES Research Report, 21, 1–13.

3.4 vallenae.timepicker.modified_energy_ratio

vallenae.timepicker.**modified_energy_ratio**(*arr*, *win_len*=100)

Modified energy ratio method for arrival time estimation.

The modifications improve the ability to detect the onset of a seismic arrival in the presence of random noise.

Parameters

- **arr** (`ndarray`) – Transient signal of hit
- **win_len** (`int`) – Samples of sliding windows. Default: 100

Return type `Tuple[ndarray, int]`

Returns

- Array with computed detection function
- Index of the estimated arrival time (max value)

References

- Han, L., Wong, J., & Bancroft, J. C. (2009). Time picking and random noise reduction on microseismic data. CREWES Research Report, 21, 1–13.

CHAPTER FOUR

EXAMPLES

A collection of examples how to read and analyse Acoustic Emission data.

4.1 Read pridb

```
import os
import matplotlib.pyplot as plt
import vallenae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
PRIDB = os.path.join(HERE, "steel_plate/sample.pridb")
```

4.1.1 Open pridb

```
pridb = vae.io.PriDatabase(PRIDB)

print("Tables in database: ", pridb.tables())
print("Number of rows in data table (ae_data): ", pridb.rows())
print("Set of all channels: ", pridb.channel())
```

Out:

```
Tables in database:  {'acq_setup', 'data_integrity', 'ae_fieldinfo', 'ae_data', 'ae_markers', 'ae_globalinfo', 'ae_params'}
Number of rows in data table (ae_data):  18
Set of all channels:  {1, 2, 3, 4}
```

4.1.2 Read hits to Pandas DataFrame

```
df_hits = pridb.read_hits()
# Print a few columns
print(df_hits[["time", "channel", "amplitude", "counts", "energy"]])
```


Out:

```
Hits: 0% | 0/4 [00:00<?, ?it/s]
Hits: 100%|#####| 4/4 [00:00<00:00, 10817.03it/s]
      time   channel   amplitude   counts       energy
set_id
10     3.992771        3     0.046539    2180  2.799510e+07
11     3.992775        2     0.059621    2047  2.276279e+07
12     3.992813        4     0.034119    1854  1.286700e+07
13     3.992814        1     0.029115    1985  1.265275e+07
```

4.1.3 Query Pandas DataFrame

DataFrames offer powerful features to query and aggregate data, e.g. plot summed energy per channel

```
ax = df_hits.groupby("channel").sum()["energy"].plot.bar(figsize=(8, 3))
ax.set_xlabel("Channel")
ax.set_ylabel("Summed Energy [eu = 1e-14 V2s]")
plt.tight_layout()
plt.show()
```



4.1.4 Read markers

```
df_markers = pridb.read_markers()
print(df_markers)
```

Out:

```
Marker: 0% | 0/5 [00:00<?, ?it/s]
Marker: 100%|#####| 5/5 [00:00<00:00, 18347.79it/s]
      time   set_type           data   number
set_id
1     0.00        6
2     0.00        4           10:52 Resume    1
3     0.00        5           2019-09-20 10:54:52  <NA>
4     0.00        4   TimeZone: +02:00 (W. Europe Standard Time)    2
18    100.07       4           10:56 Suspend    3
```

4.1.5 Read parametric data


```
df_parametric = pridb.read_parametric()
print(df_parametric)
```

Out:

```
Parametric: 0%|          | 0/9 [00:00<?, ?it/s]
Parametric: 100%|#####
time    param_id   pctd   pcta
set_id
5       0.00        1       0       0
6       1.00        1       0       0
7       2.00        1       0       0
8       3.00        1       0       0
9       3.99        1       0       0
14      4.00        1       0       0
15      5.00        1       0       0
16      6.00        1       0       0
17      6.45        1       0       0
```

Total running time of the script: (0 minutes 0.222 seconds)

4.2 Read and plot transient data



```
import os

import matplotlib.pyplot as plt

import vallenae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
```

(continues on next page)

(continued from previous page)

```

TRADB = os.path.join(HERE, "steel_plate/sample_plain.tradb") # uncompressed
TRAI = 4 # just an example, no magic here

def main():
    # Read waveform from tradb
    with vae.io.TraDatabase(TRADB) as tradb:
        y, t = tradb.read_wave(TRAI)

    y *= 1e3 # in mV
    t *= 1e6 # for μs

    # Plot waveforms
    plt.figure(figsize=(8, 4), tight_layout=True)
    plt.plot(t, y)
    plt.xlabel("Time [μs]")
    plt.ylabel("Amplitude [mV]")
    plt.title(f"Transient Wave Plot; trai = {TRAI}")
    plt.show()

if __name__ == "__main__":
    main()

```

Total running time of the script: (0 minutes 0.191 seconds)

4.3 Timepicker

Following example showcases the results of different timepicking methods. For more informations, please refer to the functions documentation ([vallenae.timepicker](#)).

```

import os
import time

import matplotlib.pyplot as plt
import numpy as np

import vallenae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
TRADB = os.path.join(HERE, "steel_plate/sample_plain.tradb")

TRAI = 4
SAMPLES = 2000

plt.ioff() # Turn interactive mode off; plt.show() is blocking

```

4.3.1 Read waveform from tradb

```
tradb = vae.io.TraDatabase(TRADB)

y, t = tradb.read_wave(TRAI)
# crop first samples
t = t[:SAMPLES]
y = y[:SAMPLES]
# unit conversion
t *= 1e6 # convert to μs
y *= 1e3 # convert to mV
```

4.3.2 Prepare plotting with time-picker results


```
def plot(t_wave, y_wave, y_picker, index_picker, name_picker):
    _, ax1 = plt.subplots(figsize=(8, 4), tight_layout=True)
    ax1.set_xlabel("Time [μs]")
    ax1.set_ylabel("Amplitude [mV]", color="g")
    ax1.plot(t_wave, y_wave, color="g")
    ax1.tick_params(axis="y", labelcolor="g")

    ax2 = ax1.twinx()
    ax2.set_ylabel(f"{name_picker}", color="r")
    ax2.plot(t_wave, y_picker, color="r")
    ax2.tick_params(axis="y", labelcolor="r")

    plt.axvline(t_wave[index_picker], color="k", linestyle=":")
    plt.show()
```

4.3.3 Hinkley Criterion

```
hc_arr, hc_index = vae.timepicker.hinkley(y, alpha=5)
plot(t, y, hc_arr, hc_index, "Hinkley Criterion")
```




Out:

```
/home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/
→importlib/_bootstrap.py:219: RuntimeWarning: numpy.ufunc size changed, may indicate_
→binary incompatibility. Expected 192 from C header, got 216 from PyObject
    return f(*args, **kwds)
```


The negative trend correlates to the chosen alpha value and can influence the results strongly. Results with **alpha = 50** (less negative trend):

```
hc_arr, hc_index = vae.timepicker.hinkley(y, alpha=50)
plot(t, y, hc_arr, hc_index, "Hinkley Criterion")
```




4.3.4 Akaike Information Criterion (AIC)

```
aic_arr, aic_index = vae.timepicker.aic(y)
plot(t, y, aic_arr, aic_index, "Akaike Information Criterion")
```




4.3.5 Energy Ratio

```
er_arr, er_index = vae.timepicker.energy_ratio(y)
plot(t, y, er_arr, er_index, "Energy Ratio")
```



4.3.6 Modified Energy Ratio

```
mer_arr, mer_index = vae.timepicker.modified_energy_ratio(y)
plot(t, y, mer_arr, mer_index, "Modified Energy Ratio")
```



4.3.7 Performance comparison


All timepicker implementations are using Numba for just-in-time (JIT) compilations. Usually the first function call is slow, because it will trigger the JIT compiler. To compare the performance to a native or numpy implementation, the average of multiple executions should be compared.

```
def timeit(callable, loops=100):
    time_start = time.perf_counter()
    for _ in range(loops):
        callable()
    return 1e6 * (time.perf_counter() - time_start) / loops # elapsed time in μs

timer_results = {
    "Hinkley": timeit(lambda: vae.timepicker.hinkley(y, 5)),
    "AIC": timeit(lambda: vae.timepicker.aic(y)),
    "Energy Ratio": timeit(lambda: vae.timepicker.energy_ratio(y)),
    "Modified Energy Ratio": timeit(lambda: vae.timepicker.modified_energy_ratio(y)),
}

for name, time in timer_results.items():
    print(f"{name}: {time:.3f} μs")

plt.figure(figsize=(8, 3), tight_layout=True)
plt.bar(timer_results.keys(), timer_results.values())
plt.ylabel("Time [μs]")
plt.show()
```



Out:

```
Hinkley: 9.432 μs
AIC: 127.979 μs
Energy Ratio: 12.150 μs
Modified Energy Ratio: 15.838 μs
```

Total running time of the script: (0 minutes 3.074 seconds)

4.4 Timepicker batch processing

Following examples shows how to stream transient data row by row, compute timepicker results and save the results to a feature database (trfdb).

```
import os
from shutil import copyfile
from tempfile import gettempdir

import matplotlib.pyplot as plt
import pandas as pd

import vallenae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
TRADB = os.path.join(HERE, "steel_plate/sample_plain.tradb")
TRfdb = os.path.join(HERE, "steel_plate/sample.trfdb")
TRfdb_TMP = os.path.join(gettempdir(), "sample.trfdb")
```

4.4.1 Open tradb (readonly) and trfdb (readwrite)

```
copyfile(TRFDB, TRFDB_TMP) # copy trfdb, so we don't overwrite it

tradb = vae.io.TraDatabase(TRADB)
trfdb = vae.io.TrfDatabase(TRFDB_TMP, mode="rw") # allow writing
```

4.4.2 Read current trfdb

```
print(trfdb.read())
```

Out:

	FFT_CoG	FFT_FoM	PA	...	CTP	FI	FR
trai				...			
2	144.042969	139.160156	59.450512	...	35	182.291672	98.019981
1	147.705078	134.277344	46.483864	...	11	222.672058	110.182449
3	155.029297	164.794922	33.995209	...	55	155.191879	95.493233
4	159.912109	139.160156	29.114828	...	29	181.023727	101.906227

[4 rows x 8 columns]

4.4.3 Compute arrival time offsets with different timepickers

To improve localisation, time of arrival estimates using the first threshold crossing can be refined with timepickers. Therefore, arrival time offsets between the first threshold crossings and the timepicker results are computed.

```
def dt_from_timepicker(timepicker_func, tra: vae.io.TraRecord):
    # Index of the first threshold crossing is equal to the pretrigger samples
    index_ref = tra.pretrigger
    # Only analyse signal until peak amplitude
    index_peak = vae.features.peak_amplitude_index(tra.data)
    data = tra.data[:index_peak]
    # Get timepicker result
    _, index_timepicker = timepicker_func(data)
    # Compute offset in us
    dt_us = (index_timepicker - index_ref) * 1e6 / tra.samplerate
    return dt_us
```

Transient data is streamed from the database row by row using `vallennae.io.TraDatabase.iread`. Only one transient data set is loaded into memory at a time. That makes the streaming interface ideal for batch processing. The timepicker results are saved to the trfdb using `vallennae.io.TrfDatabase.write`.

```
for tra in tradb.iread():
    # Calculate arrival time offsets with different timepickers
    feature_set = vae.io.FeatureRecord(
        tra=tra,
        features={
            "ATO_Hinkley": dt_from_timepicker(vae.timepicker.hinkley, tra),
            "ATO_AIC": dt_from_timepicker(vae.timepicker.aic, tra),
            "ATO_ER": dt_from_timepicker(vae.timepicker.energy_ratio, tra),
            "ATO_MER": dt_from_timepicker(vae.timepicker.modified_energy_ratio, tra),
        }
    )
```

(continues on next page)

(continued from previous page)

```
)
# Save results to trfdb
trfdb.write(feature_set)
```

4.4.4 Read results from trfdb


```
print(trfdb.read().filter(regex="ATO"))
```

Out:

	ATO_Hinkley	ATO_AIC	ATO_ER	ATO_MER
trai				
2	36.4	-0.8	-1.0	-0.4
1	30.4	-1.8	-4.0	29.2
3	67.0	-1.8	-3.2	60.4
4	65.8	-1.0	-2.2	64.2

4.4.5 Plot results

```
ax = trfdb.read()[["ATO_Hinkley", "ATO_AIC", "ATO_ER", "ATO_MER"]].plot.barh()
ax.invert_yaxis()
ax.set_xlabel("Arrival time offset [μs]")
plt.show()
```




4.4.6 Plot waveforms and arrival times

```
_, axes = plt.subplots(4, 1, tight_layout=True, figsize=(8, 8))
for row, ax in zip(trfdb.read().itertuples(), axes):
    trai = row.Index

    # read waveform from tradb
    y, t = tradb.read_wave(trai)

    # plot waveform
    ax.plot(t[400:1000] * 1e6, y[400:1000] * 1e3, "k")    # crop and convert to μs/mV
    ax.set_title(f"trai = {trai}")
    ax.set_xlabel("Time [μs]")
    ax.set_ylabel("Amplitude [mV]")
    ax.label_outer()
    # plot arrival time offsets
    ax.axvline(row.ATO_Hinkley, color="C0")
    ax.axvline(row.ATO_AIC, color="C1")
    ax.axvline(row.ATO_ER, color="C2")
    ax.axvline(row.ATO_MER, color="C3")

axes[0].legend(["Waveform", "Hinkley", "AIC", "ER", "MER"])
plt.show()
```



4.4.7 Use results in VisualAE

The computed arrival time offsets can be directly used in VisualAE. We only need to specify the unit. VisualAE requires them to be in μs . Units and other column-related meta data is saved in the `trf_fieldinfo` table. Field infos can be retrieved with `vallenae.io.TrfDatabase.fieldinfo`:

```
print(trfdb.fieldinfo())
```

Out:

```
{'FFT_CoG': {'SetTypes': 2, 'Unit': '[kHz]', 'LongName': 'F(C.o.Gravity)',  
    'Description': 'Center of gravity of spectrum', 'ShortName': None, 'FormatStr':  
    'None'}, 'FFT_FoM': {'SetTypes': 2, 'Unit': '[kHz]', 'LongName': 'F(max. Amp.)',  
    'Description': 'Frequency of maximum of spectrum', 'ShortName': None, 'FormatStr':  
    'None'}, 'PA': {'SetTypes': 8, 'Unit': '[mV]', 'LongName': 'Peak Amplitude',  
    'Description': None, 'ShortName': None, 'FormatStr': None}, 'RT': {'SetTypes': 8,  
    'Unit': '[μs]', 'LongName': 'Rise Time', 'Description': None, 'ShortName': None,  
    'FormatStr': None}, 'Dur': {'SetTypes': 8, 'Unit': '[μs]', 'LongName': 'Duration  
(available)', 'Description': None, 'ShortName': None, 'FormatStr': None}, 'CTP': {  
    'SetTypes': 8, 'Unit': None, 'LongName': 'Cnts to peak', 'Description': None,  
    'ShortName': None, 'FormatStr': '#!'}, 'FI': {'SetTypes': 8, 'Unit': '[kHz]'}}
```

(continued from previous page)

Show results as table:

```
print(pd.DataFrame(trfdb.fieldinfo()))
```

Out:

	FFT_CoG	...	FR
SetTypes	2	...	8
Unit	[kHz]	...	[kHz]
LongName	F(C.o.Gravity)	...	Reverberation Freq.
Description	Center of gravity of spectrum	...	None
ShortName	None	...	None
FormatStr	None	...	None

[6 rows x 8 columns]

Write units to trfdb

Field infos can be written with `vallenae.io.TrfDatabase.write_fieldinfo`:

```
trfdb.write_fieldinfo("ATO_Hinkley", {"Unit": "[μs]", "LongName": "Arrival Time\u2192 Offset (Hinkley)"})
trfdb.write_fieldinfo("ATO_AIC", {"Unit": "[μs]", "LongName": "Arrival Time Offset\u2192 (AIC)"})
trfdb.write_fieldinfo("ATO_ER", {"Unit": "[μs]", "LongName": "Arrival Time Offset (ER)"})
trfdb.write_fieldinfo("ATO_MER", {"Unit": "[μs]", "LongName": "Arrival Time Offset\u2192 (MER)"})

print(pd.DataFrame(trfdb.fieldinfo()).filter(regex="ATO"))
```


Out:

	ATO_Hinkley	...	ATO_MER
SetTypes	None	...	None
Unit	[μs]	...	[μs]
LongName	Arrival Time Offset (Hinkley)	...	Arrival Time Offset (MER)
Description	None	...	None
ShortName	None	...	None
FormatStr	None	...	None

[6 rows x 4 columns]


Load results in VisualAE

Time arrival offsets can be specified in the settings of *Location Processors - Channel Positions - Arrival Time Offset*. (Make sure to rename the generated trfdb to match the filename of the pridb.)



Total running time of the script: (0 minutes 0.860 seconds)

4.5 Localisation



Out:

```
/home/docs/checkouts/readthedocs.org/user_builds/pyvallennae/envs/0.4.0/lib/python3.7/
↳ importlib/_bootstrap.py:219: RuntimeWarning: numpy.ufunc size changed, may indicate
↳ binary incompatibility. Expected 192 from C header, got 216 from PyObject
    return f(*args, **kwds)

Hits: 0% | 0/4 [00:00<?, ?it/s]
Hits: 100%|#####| 4/4 [00:00<00:00, 13378.96it/s]
/home/docs/checkouts/readthedocs.org/user_builds/pyvallennae/checkouts/0.4.0/examples/
↳ ex5_location.py:122: MatplotlibDeprecationWarning: shading='flat' when X and Y have
↳ the same dimensions as C is deprecated since 3.3. Either specify the corners of
↳ the quadrilaterals with X and Y, or pass shading='auto', 'nearest' or 'gouraud', or
↳ set rcParams['pcolor.shading']. This will become an error two minor releases later.
    plt.pcolormesh(x_grid, y_grid, z_grid, cmap="cool")
Runtime for 1 call to differential_evolution(): 0.5374 s
    fun: 0.0011158880890435288
    jac: array([-0.00039993,  0.00023738])
message: 'Optimization terminated successfully.'
    nfev: 8415
    nit: 104
success: True
    x: array([0.22165228,  0.3656595 ])
```

```

import math
import os
import time
import xml.etree.ElementTree as ElementTree
from typing import Dict, Optional, Tuple

import matplotlib.pyplot as plt
import numpy as np
from numba import f8, njit
from numpy.linalg import norm
from scipy.optimize import differential_evolution

import vallenae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
SETUP = os.path.join(HERE, "steel_plate/sample.vaex")
PRIDB = os.path.join(HERE, "steel_plate/sample.pridb")
NUMBER_SENSORS = 4

@njit(f8(f8[:, :], f8, f8[:, :, :], f8[:]))
def lucy_error_fun(
    test_pos: np.ndarray,
    speed: float,
    sens_pos: np.ndarray,
    measured_delta_ts: np.ndarray,
) -> float:
    """
    Implementation of the LUCY computation in 2D as documented in
    the Vallen online help.

    Args:
        test_pos: Emitter position to test.
        speed: Assumed speed of sound in a plate-like structure.
        sens_pos: Sensor positions, often a 4x2 array, has to match
            the sorting of the delta-ts.
        measured_delta_ts: The measured time differences in seconds, has to
            match the order of the sensor positions.

    Returns:
        The LUCY value as a float. Ideally 0, in practice never 0, always positive.
    """
    m = len(measured_delta_ts)
    n = m + 1
    measured_delta_dists = speed * measured_delta_ts
    theo_dists = np.zeros(n)
    theo_delta_dists = np.zeros(m)
    for i in range(n):
        theo_dists[i] = norm(test_pos - sens_pos[i, :])
    for i in range(m):
        theo_delta_dists[i] = theo_dists[i + 1] - theo_dists[0]

    # LUCY definition taken from the vallen online help:
    lucy_val = norm(theo_delta_dists - measured_delta_dists) / math.sqrt(n - 1)

```

(continues on next page)

(continued from previous page)

```

    return lucy_val

def get_channel_positions(setup_file: str) -> Dict[int, Tuple[float, float]]:
    tree = ElementTree.parse(setup_file)
    nodes = tree.getroot().findall("./ChannelPos")
    if nodes is None:
        raise RuntimeError("Can not retrieve channel positions from %s", setup_file)
    channel_positions = {
        int(elem.get("Chan")): (float(elem.get("X")), float(elem.get("Y"))) # type:_
    }
    for elem in nodes if elem is not None
    }
    return channel_positions

def get_velocity(setup_file: str) -> Optional[float]:
    tree = ElementTree.parse(setup_file)
    node = tree.getroot().find("./Location")
    if node is not None:
        velocity_str = node.get("Velocity")
        if velocity_str is not None:
            return float(velocity_str) * 1e3 # convert to m/s
    raise RuntimeError("Can not retrieve velocity from %s", setup_file)

def main():
    # Consts plotting
    text_delta_y = 0.03
    text_delta_x = -0.12

    # Consts LUCY grid
    grid_delta = 0.01
    location_search_bounds = [(0.0, 0.80), (0.0, 0.80)]

    # Read from pridb
    pridb = vae.io.PriDatabase(PRIDB)
    hits = pridb.read_hits()
    pridb.close()

    channel_order = hits["channel"].to_numpy()
    arrival_times = hits["time"].to_numpy()
    delta_ts = (arrival_times - arrival_times[0])[1:]

    # Get localisation parameters from .vaex file
    velocity = get_velocity(SETUP)
    pos_dict = get_channel_positions(SETUP)

    # Order sensor positions by hit occurrence
    pos_ordered = np.array([pos_dict[ch] for ch in channel_order])

    # Compute heatmap
    lucy_instance_2args = lambda x, y: lucy_error_fun(
        np.array([x, y]), velocity, pos_ordered, delta_ts
    )

    x_range = np.arange(location_search_bounds[0][0], location_search_bounds[0][1],_
    grid_delta)

```

(continues on next page)

(continued from previous page)

```

y_range = x_range
x_grid, y_grid = np.meshgrid(x_range, y_range)
z_grid = np.vectorize(lucy_instance_2args)(x_grid, y_grid)

# Plot heatmap
plt.figure(tight_layout=True)
plt.pcolormesh(x_grid, y_grid, z_grid, cmap="cool")
plt.colorbar()
plt.title("Location Result and LUCY-Heatmap")
plt.xlabel("x [m]")
plt.ylabel("y [m]")

# Compute location
lucy_instance_single_arg = lambda pos: lucy_error_fun(
    pos, velocity, pos_ordered, delta_ts
)

start = time.perf_counter()
# These are excessive search / overkill parameters:
location_result = differential_evolution(
    lucy_instance_single_arg,
    location_search_bounds,
    popsize=40,
    polish=True,
    strategy="rand1bin",
    recombination=0.1,
    mutation=1.3,
)
end = time.perf_counter()
print(f"Runtime for 1 call to differential_evolution(): {(end - start):0.4} s")
print(location_result)

# Plot location result
x_res = location_result.x[0]
y_res = location_result.x[1]
plt.plot([x_res], [y_res], "bo")
plt.text(
    x_res + text_delta_x,
    y_res + text_delta_y,
    "location result",
    fontsize=9,
    color="b",
)
# Plot sensor positions
for channel, (x, y) in pos_dict.items():
    text = f"S{channel} (x={x:0.2f}m | y={y:0.2f}m)"
    plt.scatter(x, y, marker="o", color="w")
    plt.text(x + text_delta_x, y + text_delta_y, text, fontsize=9, color="w")

plt.show()

if __name__ == "__main__":
    main()

```

Total running time of the script: (0 minutes 1.433 seconds)

4.6 Go fast with multiprocessing

The streaming interfaces with iterables allow efficient batch processing as shown [here](#). But still only one core/thread will be utilized. We will change that will multiprocessing.

Following example shows a batch feature extraction procedure using multiple CPU cores.

```
import os
import time
import multiprocessing
from typing import Dict, Iterable
from itertools import cycle
import __main__

import numpy as np
from scipy import stats
import matplotlib.pyplot as plt

import vallennae as vae

HERE = os.path.dirname(__file__) if "__file__" in locals() else os.getcwd()
TRADB = os.path.join(HERE, "steel_plate/sample_plain.tradb")
```

Out:

```
/home/docs/checkouts/readthedocs.org/user_builds/pyvallennae/envs/0.4.0/lib/python3.7/
→importlib/_bootstrap.py:219: RuntimeWarning: numpy.ufunc size changed, may indicate_
→binary incompatibility. Expected 192 from C header, got 216 from PyObject
    return f(*args, **kwds)
```

4.6.1 Prepare streaming reads

```
tradb = vae.io.TraDatabase(TRADB)
```

Our sample tradb only contains four data sets. That is not enough data for demonstrating batch processing. Therefore, we will simulate more data by looping over the data sets with following generator/iterable:

```
def tra_generator(loops: int = 1000) -> Iterable[vae.io.TraRecord]:
    for loop, tra in enumerate(cycle(tradb.iread())):
        if loop > loops:
            break
        yield tra
```

4.6.2 Define feature extraction function

Following function will be applied to all data sets and returns computed features:

```
def feature_extraction(traj: vae.io.TraRecord) -> Dict[str, float]:
    # compute random statistical features
    return {
        "Std": np.std(traj.data),
        "Skew": stats.skew(traj.data),
    }
```

(continues on next page)

(continued from previous page)

```
# Fix to use pickle serialization in sphinx gallery
setattr(__main__, feature_extraction.__name__, feature_extraction)
```

4.6.3 Compute with single thread/core

Note: The examples are executed on the CI / readthedocs server with limited resources. Therefore, the shown computation times and speedups are below the capability of modern machines.

Run computation in a single thread and get the time:

```
time_elapsed_ms = lambda t0: 1e3 * (time.perf_counter() - t0)

time_start = time.perf_counter()
for tra in tra_generator():
    results = feature_extraction(tra)
    # do something with the results
time_single_thread = time_elapsed_ms(time_start)

print(f"Time single thread: {time_single_thread:.2f} ms")
```

Out:

```
Time single thread: 785.18 ms
```

4.6.4 Compute with multiple processes/cores

First get number of available cores in your machine:

```
print(f"Available CPU cores: {os.cpu_count()}")
```

Out:

```
Available CPU cores: 2
```

But how can we utilize those cores? The common answer for most programming languages is multithreading. Threads run in the same process and heap, so data can be shared between them (with care). Sadly, Python uses a global interpreter lock (GIL) that locks heap memory, because Python objects are not thread-safe. Therefore, threads are blocking each other and no speedups are gained by using multiple threads.

The solution for Python is multiprocessing to work around the GIL. Every process has its own heap and GIL. Multiprocessing will introduce overhead for interprocess communication and data serialization/deserialization. To reduce the overhead, data is sent in bigger chunks.

Run computation on 4 cores with chunks of 128 data sets and get the time / speedup:

```
with multiprocessing.Pool(4) as pool:
    time_start = time.perf_counter()
    for results in pool imap(feature_extraction, tra_generator(), chunksize=128):
        pass # do something with the results
    time_multiprocessing = time_elapsed_ms(time_start)
```

(continues on next page)

(continued from previous page)

```
print(f"Time multiprocessing: {time_multiprocessing:.2f} ms")
print(f"Speedup: {(time_single_thread / time_multiprocessing):.2f}")
```

Out:


```
Time multiprocessing: 795.72 ms
Speedup: 0.99
```

Variation of the chunksize

Following results show how the chunksize impacts the overall performance. The speedup is measured for different chunksizes and plotted against the chunksize:

```
chunksizes = (10, 40, 60, 80, 100, 120, 140, 160, 200)
speedup_chunksizes = []
with multiprocessing.Pool(4) as pool:
    for chunksize in chunksizes:
        time_start = time.perf_counter()
        for results in pool imap(feature_extraction, tra_generator(), chunksize=chunksize):
            pass # do something with the results
        speedup_chunksizes.append(time_single_thread / time_elapsed_ms(time_start))

plt.figure(tight_layout=True, figsize=(6, 3))
plt.plot(chunksizes, speedup_chunksizes)
plt.xlabel("Chunksize")
plt.ylabel("Speedup")
plt.show()
```



Total running time of the script: (0 minutes 9.246 seconds)

CHANGELOG

All notable changes to this project will be documented in this file.

The format is based on [Keep a Changelog](#), and this project adheres to [Semantic Versioning](#).

5.1 Unreleased

5.2 0.4.0 - 2021-02-14

5.2.1 Added

- CI with GitHub actions on Linux, MacOS and Windows
- Workflow with GitHub actions to publish to PyPI on new releases
- `pyproject.toml` as the main config file for pylint, pytest, tox, coverage, ...

5.2.2 Changed

- Return exact time range with `TraDatabase.read_continuous_wave`
- Return “absolute” time axis with `TraDatabase.read_continuous_wave` (instead of starting at $t = 0$ s)

5.2.3 Fixed

- Fix database close if exception raised in `__init__` (e.g. file not found)
- Example `ex6_multiprocessing` for MacOS
- Find lower/upper bounds for same values (times) in binary search (used by `TraDatabase.iread`)
- Stop condition for `time_stop` in `TraDatabase.iread`
- Use TRAI for `TraDatabase.iread` as a time sorted index for binary search (SetID is not!)
- Check for empty time ranges in `TraDatabase.iread`

5.3 0.3.0 - 2020-11-05

5.3.1 Added

- Query filter for pridb/tradb (i)read functions

5.4 0.2.4 - 2020-11-01

5.4.1 Fixed

- SQL schemas for pridb/tradb/trfdb creation, add fieldinfos

5.5 0.2.3 - 2020-09-01

5.5.1 Fixed

- AIC timepicker
- Add threshold for monotonic time check (1 ns) to ignore rounding issues
- Suppress exception chaining

5.6 0.2.2 - 2020-07-10

5.6.1 Added

- Database classes are now pickleable and can be used in multiprocessing
- SQLite transactions for all writes
- Faster blob encoding (`vallenae.io.encode_data_blob`)
- Faster RMS computation with Numba (`vallenae.features.rms`)

5.6.2 Fixed

- Catch possible global_info table parsing errors

5.7 0.2.1 - 2020-02-10

5.7.1 Fixed

- Examples outputs if not run as notebook
- Out-of-bound time_start, time_stop with SQL binary search
- Optional signal strength for e.g. spotWave data acquisition

5.8 0.2.0 - 2020-02-06

5.8.1 Added

- Database creation with mode="rwc", e.g. `vallenae.io.PriDatabase.__init__`

5.8.2 Fixed

- Number field in `vallenae.io.MarkerRecord` optional
- Scaling of parametric inputs optional
- Keep column order of query if new columns are added to the database
- Return array with float32 from `vallenae.io.TraDatabase.read_continuous_wave` (instead of float64)

5.9 0.1.0 - 2020-01-24

Initial public release

CHAPTER
SIX

TODOS

Todo: Status flag

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/io/pridb.py:docstring of vallenae.io.pridb.PriDatabase.write_hit, line 10.)

Todo: Status flag

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/io/pridb.py:docstring of vallenae.io.pridb.PriDatabase.write_parametric, line 10.)

Todo: Status flag

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/io/pridb.py:docstring of vallenae.io.pridb.PriDatabase.write_status, line 10.)

Todo: Status flag

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/io/tradb.py:docstring of vallenae.io.tradb.TraDatabase.write, line 9.)

Todo: Remove RMS

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/io/datatypes.py:docstring of vallenae.io.datatypes.TraRecord, line 3.)

Todo: Weak performance, if used with default parameter alpha

(The [original entry](#) is located in /home/docs/checkouts/readthedocs.org/user_builds/pyvallenae/envs/0.4.0/lib/python3.7/site-packages/vallenae/timepicker/timepicker.py:docstring of vallenae.timepicker.timepicker.hinkley, line 22.)

CHAPTER
SEVEN

INDICES AND TABLES

- genindex
- modindex

PYTHON MODULE INDEX

V

`vallenae.features`, 34
`vallenae.io`, 1
`vallenae.timepicker`, 38

INDEX

Symbols

`__init__()` (*vallenae.io.FeatureRecord method*), 33
`__init__()` (*vallenae.io.HitRecord method*), 22
`__init__()` (*vallenae.io.MarkerRecord method*), 24
`__init__()` (*vallenae.io.ParametricRecord method*), 29
`__init__()` (*vallenae.io.PriDatabase method*), 4
`__init__()` (*vallenae.io.StatusRecord method*), 26
`__init__()` (*vallenae.io.TraDatabase method*), 11
`__init__()` (*vallenae.io.TraRecord method*), 32
`__init__()` (*vallenae.io.TrfDatabase method*), 16

A

`aic()` (*in module vallenae.timepicker*), 40
`amplitude()` (*vallenae.io.HitRecord property*), 20
`amplitude_to_db()` (*in module vallenae.features*), 38

C

`cascade_counts()` (*vallenae.io.HitRecord property*), 20
`cascade_energy()` (*vallenae.io.HitRecord property*), 20
`cascade_hits()` (*vallenae.io.HitRecord property*), 20
`cascade_signal_strength()` (*vallenae.io.HitRecord property*), 20
`channel()` (*vallenae.io.HitRecord property*), 20
`channel()` (*vallenae.io.PriDatabase method*), 5
`channel()` (*vallenae.io.StatusRecord property*), 25
`channel()` (*vallenae.io.TraDatabase method*), 11
`channel()` (*vallenae.io.TraRecord property*), 30
`close()` (*vallenae.io.PriDatabase method*), 5
`close()` (*vallenae.io.TraDatabase method*), 11
`close()` (*vallenae.io.TrfDatabase method*), 16
`columns()` (*vallenae.io.PriDatabase method*), 5
`columns()` (*vallenae.io.TraDatabase method*), 12
`columns()` (*vallenae.io.TrfDatabase method*), 16
`connected()` (*vallenae.io.PriDatabase property*), 3
`connected()` (*vallenae.io.TraDatabase property*), 10
`connected()` (*vallenae.io.TrfDatabase property*), 15
`connection()` (*vallenae.io.PriDatabase method*), 5

`connection()` (*vallenae.io.TraDatabase method*), 12
`connection()` (*vallenae.io.TrfDatabase method*), 16
`count()` (*vallenae.io.FeatureRecord method*), 33
`count()` (*vallenae.io.HitRecord method*), 22
`count()` (*vallenae.io.MarkerRecord method*), 24
`count()` (*vallenae.io.ParametricRecord method*), 29
`count()` (*vallenae.io.StatusRecord method*), 26
`count()` (*vallenae.io.TraRecord method*), 32
`counts()` (*in module vallenae.features*), 37
`counts()` (*vallenae.io.HitRecord property*), 20
`create()` (*vallenae.io.PriDatabase static method*), 5
`create()` (*vallenae.io.TraDatabase static method*), 12
`create()` (*vallenae.io.TrfDatabase static method*), 16

D

`data()` (*vallenae.io.MarkerRecord property*), 23
`data()` (*vallenae.io.TraRecord property*), 30
`data_format()` (*vallenae.io.TraRecord property*), 30
`db_to_amplitude()` (*in module vallenae.features*), 38
`decode_data_blob()` (*in module vallenae.io*), 34
`duration()` (*vallenae.io.HitRecord property*), 21

E

`encode_data_blob()` (*in module vallenae.io*), 34
`energy()` (*in module vallenae.features*), 37
`energy()` (*vallenae.io.HitRecord property*), 21
`energy()` (*vallenae.io.StatusRecord property*), 25
`energy_ratio()` (*in module vallenae.timepicker*), 40

F

`FeatureRecord` (*class in vallenae.io*), 32
`features()` (*vallenae.io.FeatureRecord property*), 33
`fieldinfo()` (*vallenae.io.PriDatabase method*), 5
`fieldinfo()` (*vallenae.io.TraDatabase method*), 12
`fieldinfo()` (*vallenae.io.TrfDatabase method*), 17
`filename()` (*vallenae.io.PriDatabase property*), 4
`filename()` (*vallenae.io.TraDatabase property*), 10
`filename()` (*vallenae.io.TrfDatabase property*), 15
`first_threshold_crossing()` (*in module vallenae.features*), 36

```
from_sql() (vallennae.io.FeatureRecord      class    pa1() (vallennae.io.ParametricRecord property), 27
            method), 33
from_sql() (vallennae.io.HitRecord class method), 22
from_sql() (vallennae.io.MarkerRecord class method), 24
from_sql() (vallennae.io.ParametricRecord class    pa2() (vallennae.io.ParametricRecord property), 27
            method), 29
from_sql() (vallennae.io.StatusRecord class method), 26
from_sql() (vallennae.io.TraRecord class method), 32
pa3() (vallennae.io.ParametricRecord property), 28
pa4() (vallennae.io.ParametricRecord property), 28
pa5() (vallennae.io.ParametricRecord property), 28
pa6() (vallennae.io.ParametricRecord property), 28
pa7() (vallennae.io.ParametricRecord property), 28
param_id() (vallennae.io.HitRecord property), 21
param_id() (vallennae.io.ParametricRecord property), 28
param_id() (vallennae.io.StatusRecord property), 25
param_id() (vallennae.io.TraRecord property), 31
ParametricRecord (class in vallennae.io), 27
pcta() (vallennae.io.ParametricRecord property), 28
pctd() (vallennae.io.ParametricRecord property), 28
peak_amplitude () (in module vallennae.features), 35
peak_amplitude_index () (in module vallennae.features), 35
pretrigger() (vallennae.io.TraRecord property), 31
PriDatabase (class in vallennae.io), 3
G
globalinfo() (vallennae.io.PriDatabase method), 6
globalinfo() (vallennae.io.TraDatabase method), 12
globalinfo() (vallennae.io.TrfDatabase method), 17
H
hinkley() (in module vallennae.timepicker), 39
HitRecord (class in vallennae.io), 19
I
index() (vallennae.io.FeatureRecord method), 33
index() (vallennae.io.HitRecord method), 22
index() (vallennae.io.MarkerRecord method), 24
index() (vallennae.io.ParametricRecord method), 29
index() (vallennae.io.StatusRecord method), 26
index() (vallennae.io.TraRecord method), 32
iread() (vallennae.io.TraDatabase method), 12
iread() (vallennae.io.TrfDatabase method), 17
iread_hits() (vallennae.io.PriDatabase method), 6
iread_markers() (vallennae.io.PriDatabase method), 6
iread_parametric() (vallennae.io.PriDatabase method), 7
iread_status() (vallennae.io.PriDatabase method), 7
is_above_threshold() (in module vallennae.features), 36
J
K
L
M
MarkerRecord (class in vallennae.io), 23
modified_energy_ratio() (in module vallennae.timepicker), 41
module
    vallennae.features, 34
    vallennae.io, 1
    vallennae.timepicker, 38
N
number() (vallennae.io.MarkerRecord property), 23
P
pa0() (vallennae.io.ParametricRecord property), 27
pa1() (vallennae.io.ParametricRecord property), 27
pa2() (vallennae.io.ParametricRecord property), 27
pa3() (vallennae.io.ParametricRecord property), 28
pa4() (vallennae.io.ParametricRecord property), 28
pa5() (vallennae.io.ParametricRecord property), 28
pa6() (vallennae.io.ParametricRecord property), 28
pa7() (vallennae.io.ParametricRecord property), 28
param_id() (vallennae.io.HitRecord property), 21
param_id() (vallennae.io.ParametricRecord property), 28
param_id() (vallennae.io.StatusRecord property), 25
param_id() (vallennae.io.TraRecord property), 31
ParametricRecord (class in vallennae.io), 27
pcta() (vallennae.io.ParametricRecord property), 28
pctd() (vallennae.io.ParametricRecord property), 28
peak_amplitude () (in module vallennae.features), 35
peak_amplitude_index () (in module vallennae.features), 35
pretrigger() (vallennae.io.TraRecord property), 31
PriDatabase (class in vallennae.io), 3
R
read() (vallennae.io.PriDatabase method), 7
read() (vallennae.io.TraDatabase method), 13
read() (vallennae.io.TrfDatabase method), 17
read_continuous_wave() (vallennae.io.TraDatabase method), 13
read_hits() (vallennae.io.PriDatabase method), 8
read_markers() (vallennae.io.PriDatabase method), 8
read_parametric() (vallennae.io.PriDatabase method), 8
read_status() (vallennae.io.PriDatabase method), 8
read_wave() (vallennae.io.TraDatabase method), 14
rise_time() (in module vallennae.features), 36
rise_time() (vallennae.io.HitRecord property), 21
rms() (in module vallennae.features), 37
rms() (vallennae.io.HitRecord property), 21
rms() (vallennae.io.StatusRecord property), 25
rms() (vallennae.io.TraRecord property), 31
rows() (vallennae.io.PriDatabase method), 8
rows() (vallennae.io.TraDatabase method), 14
rows() (vallennae.io.TrfDatabase method), 17
S
samplerate() (vallennae.io.TraRecord property), 31
samples() (vallennae.io.TraRecord property), 31
set_id() (vallennae.io.HitRecord property), 21
set_id() (vallennae.io.MarkerRecord property), 23
set_id() (vallennae.io.ParametricRecord property), 29
set_id() (vallennae.io.StatusRecord property), 25
set_type() (vallennae.io.MarkerRecord property), 23
signal_strength() (in module vallennae.features), 37
```

signal_strength() (*vallenae.io.HitRecord property*), 21
signal_strength() (*vallenae.io.StatusRecord property*), 25
StatusRecord (*class in vallenae.io*), 24

T

tables() (*vallenae.io.PriDatabase method*), 9
tables() (*vallenae.io.TraDatabase method*), 14
tables() (*vallenae.io.TrfDatabase method*), 18
threshold() (*vallenae.io.HitRecord property*), 21
threshold() (*vallenae.io.StatusRecord property*), 26
threshold() (*vallenae.io.TraRecord property*), 31
time() (*vallenae.io.HitRecord property*), 22
time() (*vallenae.io.MarkerRecord property*), 24
time() (*vallenae.io.ParametricRecord property*), 29
time() (*vallenae.io.StatusRecord property*), 26
time() (*vallenae.io.TraRecord property*), 31
TraDatabase (*class in vallenae.io*), 10
trai() (*vallenae.io.FeatureRecord property*), 33
trai() (*vallenae.io.HitRecord property*), 22
trai() (*vallenae.io.TraRecord property*), 31
TraRecord (*class in vallenae.io*), 30
TrfDatabase (*class in vallenae.io*), 15

V

vallenae.features
 module, 34
vallenae.io
 module, 1
vallenae.timepicker
 module, 38

W

write() (*vallenae.io.TraDatabase method*), 14
write() (*vallenae.io.TrfDatabase method*), 18
write_fieldinfo() (*vallenae.io.PriDatabase method*), 9
write_fieldinfo() (*vallenae.io.TraDatabase method*), 15
write_fieldinfo() (*vallenae.io.TrfDatabase method*), 18
write_hit() (*vallenae.io.PriDatabase method*), 9
write_marker() (*vallenae.io.PriDatabase method*),
 9
write_parametric() (*vallenae.io.PriDatabase method*), 9
write_status() (*vallenae.io.PriDatabase method*),
 10